

### ***Precautionary Notes — Section 12***

The following is a listing of precautionary notes found within this Manual and otherwise. They should be noted and followed for the equipment to operate at an optimum state.

- Never probe a contact without using a mating patchcord as a test lead.
- Never forcefully engage a system if there is an excessive amount of resistance on the handle.
- Never allow an ITA to drop as this may cause misaligned engagement and/or irreparable damage.
- Always insert and extract a contact insertion/extraction tool inline with the contact. Never apply pressure to the side as this may break either contact or tool. This also applies to forming and enlarging tools.
- When engaging the ITA with the Receiver, caution must be taken to ensure that the ITA is parallel with the Receiver upon engagement and that the ITA rollers are engaged ***at the same time!***
- It is advisable that power to the Interface System be disconnected prior to handling and maintenance.
- Caution should always be used when engaging, making sure that all foreign objects are removed from the system.
- 50 OHM ITA contact engaged with 95 OHM Receiver contact will damage the 95 OHM contact.
- Use care when hinging Receiver down. Always maintain hand contact to prevent Receiver from dropping suddenly, resulting in damage to the system.